

marantz



CINEMA 30

CINEMA 30 AV Receiver

CINEMA 30 is the most refined AVR Marantz has created. With premium features, optimized from decades of rich heritage, timeless style, and engineered for utmost performance, Marantz CINEMA 30 is the foundation of superior home theater systems.

- **High Power & Low Distortion**
Each channel is rated at 140W with 0.05% THD, making both powerful dynamics and subtle detail a reality.
- **11 Channels & Countless Configurations**
Though 11 amplifier channels are built in, CINEMA 30 can process up to 13.4 channels, making the perfect speaker layout for your room easy to achieve.
- **No Compromise Engineering**
Hi-Fi performance technologies like HDAM SA-2, monolithic symmetrical amplifiers, toroidal transformer-based power supplies, and more elevate CINEMA 30 to performance levels seldom found in an AVR.
- **Sound Master Tuned & Calibrated for You**
Premium and custom ingredients are chosen by the Marantz Sound Masters to capture The Most Musical Sound. Powerful calibration and tuning tools are included, enabling you to get the best performance from your system.
- **Compatibility**
7 HDMI inputs, plus digital, analog, and phono inputs – even analog video plus loudspeaker and pre-amp outputs – ensure connectivity to virtually any components you have.
- **Timeless Yet Modern Style**
Excellence is heard and seen. CINEMA 30 is meticulously crafted in Japan with authentic materials in a modern style, befitting its rich heritage and stunning performance.



The Most Musical Sound

CINEMA 30

Technical Specifications



Multichannel Surround	
DTS HD Master / DTS:X / DTS:X Pro / DTS Neo:6 / DTS Neural:X / DTS Virtual:X	Yes / Yes / Yes / No / Yes / Yes
IMAX Enhanced	Yes
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization / Dolby Atmos Music / Dolby ProLogic II / Dolby Surround	Yes / Yes / Yes / Yes / No / Yes
Auro 3D	Yes
360 Reality Audio / MPEG H	Yes / Yes
Audyssey DSX	No
Multichannel Stereo	Yes
Max. Number of Processing (Preamp) Channels	13.4
Sound Enhancements	
Discrete Power Amplifier	Yes
Copper Plated Chassis	Yes
Power Transformer: Toroidal / EI	Toroidal
Current Feedback Topology	Yes
Hyper Dynamic Amplifier Modules (HDAM)	Yes
Pure Direct	Yes
Gold Plated RCA Terminals	Yes
Clock Jitter Reducer	Yes
Audyssey	MultEQ XT32
Audyssey Dynamic EQ / Dynamic Volume / Audyssey LFC	Yes / Yes / Yes
Dirac Live upgradability	Yes
Compressed Audio Enhancer: MDAX2	Yes
Network	
HEOS Multi-Room and Streaming	Yes
Bluetooth Re-Transmit for Bluetooth headphones	Yes (with volume control)
Alexa / Google Voice Assistant / Apple HomePod	Yes / Yes / Yes
Network Audio Sharing	Yes
Lossy Formats: MP3 / WMA / AAC	Yes / Yes / Yes
Lossless Formats: FLAC / ALAC / WAV	Yes / Yes / Yes
Lossless formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	Yes / Yes / Yes
DSD Audio Streaming	Yes, 2.8/5.6 MHz
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	Yes / Yes / Yes
Gapless Playback	Yes (FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming	Yes (AirPlay 2)
Internet Radio	Yes (TuneIn)
Spotify	Yes (Spotify Connect)
Pandora / SiriusXM	Yes / Yes
Other Streaming Services	Amazon Music HD / Amazon Music / TIDAL / Deezer / iHeart Radio / Napster / Soundcloud / Mood Mix
Roos tested	
Compatible with Remote App for Smart Phones	Marantz AVR Remote
Compatible with Remote App for Tablets	Android / iOS / Amazon Kindle
Wi-Fi / Bluetooth / Ethernet Ports	Yes / Yes / Yes
HDMI	
HDMI Inputs: Back / Front	Yes
HDCP 2.3 Support	Yes
HDMI Outputs: Main / Zone	Yes
Video Conversion Analog → HDMI	Yes
Analog to HDMI Scaling	Yes
HDMI to HDMI Scaling	Yes
GUI Overlay on HDMI	Yes
HDMI 2.1: 8K/60Hz AB / 4K/120Hz AB	Yes
8K/60Hz AB / 4K/120Hz AB Pass-through In/Out	Yes
HDMI 2.0: 3D / 4K / CEC / ARC	Yes
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR	Yes
HDMI	
ALLM (Auto Low Latency Mode) Pass-through for Gaming	Yes
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching	Yes / Yes / No
3D Signal Pass-through	Yes
8K Signal Pass-through / Scaling / GUI Overlay	Yes / Yes / Yes
4K Signal Pass-through / Scaling / GUI Overlay	Yes / Yes / Yes
HDMI Pass-through in Standby Mode	Yes
Picture Adjust / Noise Reduction	No / No
CEC	Yes
DSD Audio Capability	Yes
Audio Return Channel	ARC, eARC
Auto LipSync	Yes

Multiroom / CI		
HEOS Multi-Room Integrated	Yes	
HEOS Link Compatibility: IR / IP	Yes / Yes	
Multi-Room zones	3	
Zone Audio Source: HDMI / Opt. Coax / Network, USB / Analog	Yes (2ch) / Yes (2ch) / Yes / Yes	
Zone Audio Output: Speaker / Preout	Yes / Yes	
Zone HDMI Output from HDMI Source	Yes	
IP Control / RS232 Control / Web Control / App Control	Yes / Yes / Yes / Yes	
IR Flasher In	Yes	
Marantz Remote Bus	Yes	
DC Trigger Output	3	
HDMI Diagnostics	Yes	
Inputs/Outputs		
Video	Composite In / Out	2 / 0
	Component In / Out	1 / 0
	HDMI In / Out	7 / 3
	Multi-Room Video Out: Video / HDMI	No / Yes
Audio	Analog In / Out	6 / 0
	Phono (MM) In	Yes
	Digital In: Optical / Coaxial	2 / 2
	Multi-Room Out: Analog / Digital	2 / 0
	Multichannel Pre Out	Yes (13.4)
	Subwoofer Out	4 (independent)
Other	7.1 Multichannel Input	No
	Speaker Terminal: Gold Plated Screw / Regular Screw	Yes / No
	Number of Speaker Terminals	13
	Speaker A / B	Assignable
	Bi-Amp Drive	Assignable
	Multi-Room Speaker Terminal	Assignable
	Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB	No / No / No / No / Yes
	USB Audio / Made for iPod / Made for iPhone	Yes / No / No
	USB Power supply on rear panel	Yes
	AM/FM Tuner	Yes
Specifications		
Number of Poweramps	11	
Power Output	8 ohm, 20 Hz - 20 kHz, 0.08% 2ch Drive	N/A
	8 ohm, 20 Hz - 20 kHz, 0.05% 2ch Drive	140 W
	6 ohm, 1 kHz, 0.7% 2ch Drive	175 W
	6 ohm, 1 kHz, 10% 1ch Drive	250 W
70% Guarantee	Yes	
Others		
Auto Speaker Setup by Microphone	Audyssey MultEQ XT32 Dirac Live (upgrade)	
Front Display	2 line FLD + port hole OLED	
Graphic User Interface - GUI	Modern HD GUI	
ISF Certification	No	
GUI Languages	3	
Setup Assistant	Yes	
Smart Select	Yes	
Firmware Update by Network / USB	Yes / Yes	
Variable Crossover / Optimized Bass Redirection / Bass Sync	Yes / Yes / Yes	
ECO Mode / Auto Power Off / Sleep Timer	Yes / Yes / Yes	
General		
Metal Front Panel	Yes	
System Remote Control	RC051SR	
Pre-Programmed / Learnable / LCD Display	Yes / Yes / Yes	
Consumption	Power	780 W
	Power, No Sound (ECO on / off)	65 W / 110 W
	Standby	0.2 W
	CEC Standby	0.5 W
	Network Standby / Network Control, ON	Less than 2.0 W (TBD)
Maximum Dimensions	Antenna, Horizontal: (W × D × H)	17.4 × 18.0 × 7.5 in.
	Antenna, Vertical: (W × D × H)	17.4 × 18.0 × 10.2 in.
	w/o Antenna: (W × D × H)	17.4 × 17.6 × 7.5 in.
What's in the box	Main unit, remote control, batteries, AM/FM antennas, wire labels, quick start guide, Audyssey microphone, cardboard microphone stand, 2 External Detachable Antennas, AC cord	
Weight in lbs.	42.8	
UPC	747192140434 (U1B) 747192140441 (U1SG)	

Design and specifications are subject to change by Marantz without notice.

www.marantz.com