

POWER REFERENCE AMPLIFIER

1500Watt 5-Channel

MEMPHIS
AUDIO
Sixty Years
65-25



Removable
Top Mount
Control Panel



Down Firing
Accent Lights

FEATURES

- Compact space saving design
- Blue LED top cover & ground lighting
- Extruded aluminum heatsink
- 12dB/octave butterworth crossovers
- Variable EQ boost 0-12db
- 18dB subsonic filter
- Top mount controls hidden under panel
- Selectable amp turn on
- Bass knob included



POWER REFERENCE AMPLIFIER

PRX1500.5V2

5-CH 125x4 @ 2Ω / 1000Wx1 @ 1Ω Amplifier

SPECIFICATIONS

MODEL NUMBER	RMS 4Ω	RMS 2Ω	RMS 1Ω	RMS Bridged 4Ω	THD %	Signal Noise Ratio	Freq Response	Dimensions (In)	Input Range	Amp Kit
PRX1500.5V2	75x4+400	125x4+700	N/Ax4+1000	250Wx2 + N/A	<1%	>80dB	10Hz-21kHz	11.75x5.7x2.16	200mV-6V LOW 0.8V-20V HIGH	OGKIT

*Can Also Be Ran 1500W: 125x4 @ 2Ω + 1x1000 @ 1Ω